

# SRM 2150

## Modular RF Matrix Switching System (950-2150 MHz)



### General Description:

The **SRM 2150** is a matrix switch and switching subsystem that allows any of 16 to 256 inputs carrying RF signals to be routed to any of 16 to 256 outputs. The system utilizes patented stack-and-tier technology which offers ultra-reliable, high-performance, in a compact, modular design. This greatly reduces the size and complexity of the system while greatly enhancing the system's reliability by eliminating the need for patch panels and repetitive mechanical connections. The system is controllable either locally via the front panel keypad or remotely via computer and is compatible with most monitoring and control systems. The rear panel design facilitates structured cable routing, thereby eliminating confusing tangles and bundles of cables.

### Specifications:

<b>Frequency:</b>	950-2150 MHz
<b>Impedance:</b>	75 $\Omega$
<b>Max. Total Operating Input Power:</b>	-20 dBm
<b>Insertion Loss:</b>	0 $\pm$ 2 dB
<b>Frequency Response:</b>	$\pm$ 3 dB
<b>Isolation (input-to-input):</b>	$\geq$ 45 dB
<b>Isolation (output-to-output):</b>	$\geq$ 45 dB
<b>Isolation (input-to-output):</b>	>40 dB
<b>Return Loss:</b>	>10 dB
<b>RF Connectors:</b>	Type "F", 75 $\Omega$ (BNC, SMA, or N optional)
<b>Power Requirements:</b>	100-240 VAC, 50/60 Hz. Dual AC inputs and dual internal PSUs for redundancy.
<b>Power Consumption:</b>	Controller-UCM 9W Input Distribution Module-SRD 13W Matrix Switch Module-SRM 39W Output Switch Module-SRO 24W
<b>Local Control:</b>	Front panel keypad with LCD display
<b>PC Remote Control:</b>	RS-232, RS-422/485, or ETHERNET via customer-supplied PC
<b>Inter-Module Control Data:</b>	Synchronous serial
<b>Mechanical:</b>	3 RU (5.25" H x 19" W x 20" D)
<b>Software:</b>	Basic IBM-compatible operating software and system protocol included with system
<b>Available Sizes:</b>	Any configuration up to and including 256 x 256 outputs